
SLU-0200 Phase Monitor Relays (3-Phase Monitors) provide cost-effective protection against premature equipment failure caused by voltage faults on 3-Phase systems (Wye or Delta). The SLU-0200 Series multi-mode phase monitoring relay, was designed for the convenience of electrician's, maintenance managers and engineers. This device can be easily adjusted for the voltage, imbalance percentage and time delay requirements to protect against unbalanced voltages or single phasing regardless of any regenerative voltages.

Both **DELTA** and **WYE** systems may be monitored. In Wye systems, connections to neutral are NOT required. The SLU-0200 Series is UL Listed under UL File Number E55826.


NOTE: Can be used for most generator applications. Not recommended for variable frequency drive applications. Call technical support for application assistance.

AUTO RANGING	Frequency	Nominal Line-to-Line Voltages	Adjustable Range
SCALES	60Hz	208, 220, 240, 380,	200-250
		415, 440, 460, 480	360-500
	50Hz	208, 220, 240	200-250
		346, 380, 415	330-430
VOLTAGE BAND	Drop-out	±10% of Range Settin	
	Pick-up	±7% of Range Setting	g (Under/Over)
MAXIMUM VOLTAGE	550 VAC (Li	ne-to-Line)	
PHASE SEQUENCE	ABC (Will No	t Operate On CBA Sequen	ce)
POWER REQUIRED	90VA Max.		
PHASE	2% to 10%,	Adjustable Drop-out	
UNBALANCE	Hysteresis	10% of Setting	
PHASE SHIFT	13° Drop-ou	it, 12° Pick-up (Ø-Loss)	
FREQUENCY SHIFT	Not Detected	i	
RAPID CYCLE	5 Cycle Lock	out, 30 minute cycle cour	nt reset
RESET	Automatic		
RESET RELAY OUTPUT		240VAC Resistive, 1/2 H	IP @240VAC
-		Flashing	IP @240VAC
RELAY OUTPUT	SPDT, 10A @		Continuous Relay
RELAY OUTPUT	SPDT, 10A @ Normal (Green LED)	Flashing Fault Delay Active	Continuous Relay Energized
RELAY OUTPUT	Normal (Green LED)	Flashing	Continuous Relay Energized Relay
RELAY OUTPUT INDICATORS	Normal (Green LED) Fault (Red LED)	Flashing Fault Delay Active Restart Delay Active	Continuous Relay Energized
RELAY OUTPUT	Normal (Green LED) Fault (Red LED) Power Up	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum	Continuous Relay Energized Relay De-energized
RELAY OUTPUT INDICATORS	Normal (Green LED) Fault (Red LED) Power Up Fault Delay	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab	Continuous Relay Energized Relay De-energized
RELAY OUTPUT INDICATORS	Normal (Green LED) Fault (Red LED) Power Up	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustate 1 SEC. (Phase-Loss, U	Continuous Relay Energized Relay De-energized
RELAY OUTPUT INDICATORS	Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustate 1 SEC. (Phase-Loss, UPhase Reversal)	Continuous Relay Energized Relay De-energized
RELAY OUTPUT INDICATORS RESPONSE	Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustate 1 SEC. (Phase-Loss, UPhase Reversal) 0.5 to 300 S, Adjustate	Continuous Relay Energized Relay De-energized ole Inbalance or
RELAY OUTPUT INDICATORS RESPONSE TEMPERATURE	Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault Restart Operate	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustate 1 SEC. (Phase-Loss, UPhase Reversal) 0.5 to 300 S, Adjustate 32° to 131°F (0° to -10°)	Continuous Relay Energized Relay De-energized ole Inbalance or ole (Auto Reset)
RELAY OUTPUT INDICATORS RESPONSE TEMPERATURE RATINGS	Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault Restart Operate Storage	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustal: 1 SEC. (Phase-Loss, UPhase Reversal) 0.5 to 300 S, Adjustal: 32° to 131°F (0° to 4-49° to 185°F (-45° t	Continuous Relay Energized Relay De-energized ole Inbalance or ole (Auto Reset)
RELAY OUTPUT INDICATORS RESPONSE TEMPERATURE RATINGS REPEAT ACCURACY	Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault Restart Operate Storage 1% @ Fixed	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustate 1 SEC. (Phase-Loss, U Phase Reversal) 0.5 to 300 S, Adjustate 32° to 131°F (0° to 40° to 185°F (-45° te 185°F)	Continuous Relay Energized Relay De-energized Ole Inbalance or Ole (Auto Reset) H-55°C) To +85°C)
RELAY OUTPUT INDICATORS RESPONSE TEMPERATURE RATINGS	Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault Restart Operate Storage	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustal: 1 SEC. (Phase-Loss, UPhase Reversal) 0.5 to 300 S, Adjustal: 32° to 131°F (0° to 4-49° to 185°F (-45° t	Continuous Relay Energized Relay De-energized Ole Inbalance or Ole (Auto Reset) H-55°C) To +85°C)




Universal Phase Monitor w/ Rapid Cycle Lockout

TOP LABEL



DIMENSIONS (INCHES)



ORDERING INFORMATION

MODEL NUMBER	DESCRIPTION
SLU0200	Voltage/Phase Monitor